

Smart Living Lab: Access to the network drives and printing with Windows

Versio	n Date	Description
1.0	23.11.2015	Document creation
1.1	04.12.2015	General enhancement
1.2	16.12.2015	Update chapter 3
1.3	07.12.2017	New connection method
1.4	19.05.2022	New printer connection method
1.5	01.06.2022	New printer connection procedure for EPFL users
1.6	10.06.2022	Specification of the users concerned by each procedure + english translation
1.7	19.08.2022	New link for printer driver for chapter 1 section 3
1.8	15.12.2022	Renamed print server and file server
1.9	10.01.2023	Added username format section and corrected typos
1.10	11.01.2023	Corrected printer driver links
1.11	12.01.2023	Add macOS support and simplified procedure for EPFL computers
1.12	09.05.2023	Corrected print server link



Table of Contents

1	Credentials format	3
1.1	Save credentials on Windows	3
2	First connection to the network drives and to printers	5
2.1	Network drives for Windows	5
2.2	Network drives for macOS	6
2.3	Printers for Windows	8
2.4	Printers for macOS	9
3	Network drive usage	. 18
4	Printers usage	. 19



1 Credentials format

Depending on the school you belong to, you will have a different username format.

For HEIA users, this is the same username and password you use at HEIA.

For **EPFL** users, your username is the one you have at EPFL. For the password, it is **not** the password you use at EPFL (gaspar). It is the one you were given when you arrived at SLL or that you changed afterwards.

For users from the **University of Fribourg**, your username and password are the ones you were given when you arrived at the SLL. You may have changed your password at a later date.

If you have forgotten your password, you can reset it at the following address: <u>https://support.smartlivinglab.ch/</u>

HEIA users must change their password at <u>https://my.hes-so.ch/pwm/private/login</u>

1.1 Save credentials on Windows

To save your credentials on Windows, follow this procedure:

1. Open the Windows start menu and look for "Credential Manager":





2. Click on "Windows Credentials" and then on "Add a Windows credential":

→ * ↑	rol Panel > User Accounts > Credential Manager	
ontrol Panel Home	Manage your credentials	
	View and delete your saved logon information f	or websites, connected applications and networks.
	Web Credentials	Windows Credentials
	Back up Credentials Restore Credentials	Add a Windows contential
	Back up Credentials Restore Credentials Windows Credentials	Add a Windows credential
	Back up Credentials Restore Credentials Windows Credentials slipm10	Add a Windows credential Modified: Today 📀
	Back up Credentials Restore Credentials Windows Credentials sllpm10 Certificate-Based Credentials	Add a Windows credentia Modified: Today 😔 Add a certificate-based credential
	Back up Credentials Restore Credentials Windows Credentials sllprn10 Certificate-Based Credentials No certificates.	Add a Windows credential Modified: Today 📀 Add a certificate-based credential
	Back up Credentials Restore Credentials Windows Credentials sllprn10 Certificate-Based Credentials No certificates. Generic Credentials	Add a Windows credential Modified: Today Add a certificate-based credential Add a generic credential
	Back up Credentials Restore Credentials Windows Credentials sllprn10 Certificate-Based Credentials No certificates. Generic Credentials virtualapp/didlogical	Add a Windows credential Modified: Today Add a certificate-based credential Add a generic credential Modified: Today

3. In the "Internet or ..." field enter **sllprn10.sll.smartlivinglab.ch\FollowMe**, in the "User name" field enter **sll\yourUsername** and finally in the "Password" field enter your password and press ok:

🧕 Add a Windows Credential	
← → ▼ ↑ 🔯 ≪ Cred → Add a Windows Cred → Ö	م ا
Type the address of the website or netw Make sure that the user name and password that yo Internet or network address (e.g. myserver, server.company.com): User name: Ill/jeremy.s Password:	ork location and your credentials I type can be used to access the location. martlivinglab.ch\FollowMe amba
	OK Cancel

4. Repeat this operation but this time use **sllfs10.sll.smartlivinglab.ch** in the address field.



2 First connection to the network drives and to printers

2.1 Network drives for Windows





Enter your username with the following format: sll\username Then type in your password.	Windows Security Enter network credentia	×
You can check the "Remember my credentials" box to avoid having to reenter your password next time.	Enter your credentials to conne sllfs10.sll.smartlivinglab.ch sll\pierre.dupont	ect to:
You should have received a welcome email containing your username and your password. Finally, click on "OK". The drive S: is now mapped.	Domain: sll Remember my credentials OK	Cancel

2.2 Network drives for macOS

Open the Finder and select "Go" in the toolbar. Then select "Connect to	Finder File Edit View Go Window	Help
	Forward	жà
Server"	Select Startup Dis	lisk �#▲
	() Recents	AWE
	B Documents	0.00
		☆ #D
	Downloads	T#L
	Home	ФЖН
	Computer	4#C
	MirDrop	Ω # R
	🛞 Network	Фжк Станала с с с с с с с с с с с с с с с с с с
	Cloud Drive	e 分光 bizhub_colour_se ries 120
	E Shared	₩S
	Applications	s 🛇 🛪 A
	X Utilities	0 % U
	Recent Folders	MacBook Pro de TestUser
	Go to Folder	A#G
	ou to relation	5 66 0
	Connect to Server	er %K Shared
	Connect to Server	er 3 K Shared
	Connect to Serve	er 24 K Shared
In the new window, type	Connect to Server	er 24 K Shared
In the new window, type	Connect to Server	er 24 K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL	Connect to Server	er 24K shared Connect to Server ivinglab.ch/SLL
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Connect to Server	er 24K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Connect to Server	er 26K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv	er 26K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv Favourite Servers:	er 24K shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv Favourite Servers:	er 24K Shared © AirDrop Connect to Server ivinglab.ch/SLL
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv	er 24K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv	er 24K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	smb://sllfs10.sll.smartliv	er 24K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	smb://sllfs10.sll.smartliv	er 24K Shared
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv Favourite Servers:	er. 24K Shared © AirDrop Connect to Server ivinglab.ch/SLL V
In the new window, type smb://sllfs10.sll.smartlivinglab.ch/SLL and press "Connect"	Smb://sllfs10.sll.smartliv Favourite Servers:	er. 24K Shared © AirDrop Connect to Server ivinglab.ch/SLL Browse Connect



Again, click on "Connect"		You are "silfs Ca	e attempt the 10.sll.sm :lick Conne ncel	ting to co server artlivingla ct to contin	nnect to ab.ch". uue. nnect			
Select "Registered User" and enter your SLL credentials (refer to chapter 1 if you are not sure what they are).	İ İİ	Enter you "sllfs10.sl Connect Nar Passwo	Ir name an I.smartlivin As: Gu O Re me: sll\jer ord: •••• nember thi	d password nglab.ch". iest gistered U remy.gamb s password	d for the se ser a d in my key Cancel	erver chain Connect		
You can now use the SLL shared folder.	Favourites (© AirDrop (© Recents (Applications (Comments (Comments) (Co	< > SLL Shar Administration Halle Expérimentation Halle Silprn10.Ink	ed Building2050 MEP	MacBook P CISBAT	ro de TestUser Commission scientífique Projets	Scanner	C v SLL Direction SLB	Q +



2.3 Printers for Windows

To connect the printers, click one the "Start" icon. Then, type in: \\sllprn10.sll.smartlivinglab.ch\FollowMe In the search field. Press on your enter key	Ф	م مر	\\sllprn1	0.sll.smartliving	lab.ch\FollowMe
Press on your enter key.	▶ ■	Q		Archive	Downloads

Once again, you need to enter your credentials as you did before: sll\username and the password you received by email.	Windows Security Enter network credentials Enter your credentials to connect a sllfs10.sll.smartlivinglab.ch sll\pierre.dupont Domain: sll Remember my credentials	to:
	ОК	Cancel



When you see the following window, the printer is correctly installed	Follow_Me on sllprint.sll.sn Printer Document View	nartlivinglab.ch		- 0
installed.	Document Name	Status	Owner	Pages

2.4 Printers for macOS

Copy the printer driver from the SLL shared folder. You will find the driver file following this path:

SLL/Administration/Informatique/Printers/IT6PSMACOS_508AMU.dmg

•••	< > Downloads	:=	\$	Ů ⊘ ⊖·	Q
Favourites	Name	Size	Kind	Date Added	~
AirDrop	IT6PSMACOS_508AMU.dmg	100 MB	Disk Image	Today, 13:12	
ecents					
Applications					
Desktop					
Documents					
Ownloads					
Locations					
iCloud Drive					
🖂 Google 🛳					
Tags					
• Red					
• Orange					
• Yellow					

Open the driver file:

•••	< > Downloads		\equiv \$		₾ ⊘	
Favourites	Name	Size	Kind		Date Added	~
AirDrop	IT6PSMACOS_508AMU.dmg	10	00 MR Disk Im	ade	Today, 13:1	2
ecents		Open				
Applications		Open With		>		
🚍 Desktop		Move to Bin				
Documents		Get Info				
Ownloads		Rename				
Locations iCloud Drive Google		Compress "IT6PSMACOS_E Duplicate Make Alias Quick Look	508AMU.dmg"			
 ⊟ IT6 ▲ □ hefrifs ▲ 		Copy Share				
Wetwork						
Tags		1ayo		_		
	Deskton & Dock	Quick Actions		>		



In your Finder under "Locations", click on the driver:











Click on "Install":

Click on "Agree":





Enter your credentials (the ones of your mac, not the SLL ones) and click on "Install Software":

Name		lified Size
 Introduction Read Me Licence Destination Select Installation Type Installation Summary 	Installer Installer is trying to install new software. Enter your password to allow this. TestUser Install Software Cancel	computer. Ilation of this software
	Customise	Go Back Install

Click on the top right apple and select "System Settings...":

System Settings File	e Edit \	/iew Window	Help
About This Mac			
System Settings			(+)
App Store	5 updates		
Recent Items	>	•	
Force Quit System Settings	乙分第〇乙		
Sleep			
Restart			** 1
Shut Down			
Lock Screen	^ 	2	C I O Search
Log Out TestUser	☆ ₩ G	2	
			(i) Access
			Loca 📴 Contro



Click on "Add Printer, Scanner of Fax..." to add a new printer:



Then press the control key and click on the right of the toolbar. A contextual menu should appear. Select "Customise Toolbar...":

	Ac	dd Printer					
	ē		ſ	Ĩ.	~	Icon and To Icon Only	ext
Q Search						Text Only	
Name			~	Kind		Customise	Toolbar
Brother DCP-L3550CDW series Brother MFC-J6910DW @ Mac DQVENVITESSE @ MacBook P EPSON ET-2810 Series EPSON WF-2530 Series @ Ma FollowMe @ MacBook Air de T FollowMe @ MacBook Air de T FollowMe Client @ MacBook Pr HEIA FollowMe @ MacBook Pr HP Color LaserJet MFP M3770 HP ColorLaserJet MFP M182-N HP ENVY 5000 series @ MacB	es @ MacBo Book Pro S Iro Solene IcBook Air d ihibault Iro (4) o (5) Mw @ MacBo W185 @ Mac Book Pro de	ook Air-4.loc colene de Thibault pook Air de T cBook Air-4 Diego	hik I.lo	Bonjour Bonjour Bonjour Bonjour Bonjour Bonjour Bonjour Bonjour Bonjour Bonjour	Share Share Share Share Share Share	ed ed ed ed ed ed	
Name: Location: Use:							
?							Add



Drag the "Advanced" b	utton to your toolbar ar	nd click on "Don	e":		
		Add Pr	inter		
		r and a second s			
			ලුංග යැනු		
	Drag your favourite items in	to the toolbar			
	Ē		Ē	£03403	
	Windows	IP	Default	Advanced	
	Space	Flexible Space			
	or drag the default set int	to the toolbar.			
	Default IP Windows				
Show Icon Only 📀 Done					
Configure the printer a	nd chose "Select Softwa	are":			
		Add Pri	nter		
		6 @	r ¢o		
	Type: Window	/s printer via spoolss			
	Device: Another	r Device			
	URL: smb://sll	prn10.sll.smartlivingla	b.ch/FollowMe		
	Name: sllprn10	0.sll.smartlivinglab.ch			
	Use V Choo	se a Driver			
	Auto	Select			
	? Gene	ric PostScript Printer			
	Gene	ric PCL Printer			
	Selec	t Software			
	r votre produi Other	r			



Select the "KONICA MINOLTA C750i PS" driver from the list:

	Q Filter
KONICA MINOLTA C3350i PS	
KONICA MINOLTA C360i PS	
KONICA MINOLTA C4000i PS	
KONICA MINOLTA C4050i PS	
KONICA MINOLTA C450i PS	
KONICA MINOLTA C550i PS	
KONICA MINOLTA C650i PS	
KONICA MINOLTA C750i PS	
Oki 24-Pin Series	
Oki 9-Pin Series	
Zebra CPCL Label Printer	
7ahra EDI 1 I ahal Drintar	

Then configure the driver:



Setting up 'sllprn10.sll.smartlivinglab.ch...'

Make sure your printer's options are accurately shown here so you can take full advantage of them.

Paper Source Unit:	LU-303	0
Finisher:	FS-540	()
Punch Unit:	PK-526 (2/4-Hole)	©
Z-Fold Unit:	None	()
Post Inserter:	None	©
Security Document Setting:	Do Not Release Secure Print	©
	🗸 Storage	
	Secure Print Only	
	Allow Public User	
	✓ Paper Settings for Each Transmission	ay



When printing at SLL, make sure you're using the correct printer:

Caracter and the second	Printer	SIIprn10.sll.smartlivinglab.ch (SLL) ᅌ
CENTRE DE TÉLÉCHARGEMENT	Presets	None 📀
	Copies	1 \$
Télécharget ins deminent plates, manuels et lagiciets pour vos épigements foncia lehoda.	Pages All 2 Pages Range from Selection Select pages from the sid	1 to 1
Page 1 of 2	Paper Size	A4 210 by 297 mm ᅌ
Device Device Telescond Strate A	Orientation	🔾 🖈 Portrait 🔷 🕬 Landscape
Fabricler site paids Codecar so this per dage (Channes you and an and an Codecar so this per dage (Channes you and Channes) (Channes you and Channes)	Scaling	100% 🗘
	✓ Safari	
		Print backgrounds Print headers and footers
Tersis Scotters Serger terses Serger Serger terses Serger terses have been been been been been been been be	> Lavout	
Page 2 of 2	? PDF -	Cancel Print

You will be prompted to enter your credentials. Here you need to use your SLL credentials (refer to chapter 1 if you are not sure what they are). Also make sure to tick the "Remember this password in my keychain" so you won't have to configure it again:

Enter your na "sllprn10.sll.s	me and password for the printer martlivinglab.ch".
 Name:	sll\jeremy.gamba
Password:	•••••
🗹 Rememi	per this password in my keychain
	Cancel OK



3 Network drive usage

In the Windows file explorer, open the drive S:\

When signing out of your Windows session (or when restarting your computer), this drive may be shown as disconnected. You need to double click on it and enter once again your credentials

Windows Security			
Enter network credentials			
Enter your credentials to connect	to: sllfs10.sll.smartlivinglab.ch		
sll\pierre.dupond	×		
Remember my credentials			
ОК	Cancel		



4 Printers usage

This section shows how to use the SLL printers.

For some versions of Windows, you need to re-authenticate before printing. To do so, simply double click on the shortcut looking like this:



You will find this shortcut at the root of your S:\ drive. Double click on it or copy/paste it on your desktop. This is only required when restarting your computer. You only have to do this the first time after reopening your session.

Procedure

- 1. Double click on the "sllprn10" icon.
- 2. When you're printing from a software, chose the "FollowMe on sllprn10.sll.smartlivinglab.ch" printer.
- 3. Go to a Konica Minolta printer in the Smart Living Lab, pass your badge on the reader provided for this purpose. Your documents get printed.

If you do not have your badge with you, you can still print by manually authenticating on the printer with your username (without the prefix sll\ !) and your password.